

General Description:



Soundco sound mixer model DM6-FX has two microphone inputs and four stereo input channels, equipped with 48V phantom switch and 16 channel effect. This mixer has major audio recording and playback through USB port and connection through Bluetooth.

Technical Features:



device type: Desktop mixer
 Microphone channel: 2 channels
 Stereo channel: 4 channels
 Entrance port: RCA, TRS, TS, USB, XLR
 Output port: RCA, TRS, TS
 AUX output:
 A line with a separate volume
 Equalizer type:
 7 graphic lines, three volumes
 below, midrange and bass
 Effect type: 16 selective channels
 Media player information:
 Bluetooth, folder search, USB port, recorder