

PM-6500 PA Amplifier

General Description:

Soundco PM-6500 Echo Amplifier with real power of 500 watts in two categories of ohmic and volt output and 6 selective zones with separate volume control volume is designed and supplied for connecting all kinds of ceiling, column and decorative speakers. Using it in a rack mount format is one of the characteristics of a standard amplifier, which adds to the beauty of this product in combination with aluminum panel.



Technical Features:

device type: Rack mount, desktop

Amplifier type: H CLASS

Amplifier power: 500 watts

Variable power in the voltage line: 100 volt line, 70 volt line

Zoning: 6 selective zones, Microphone channel: 3 channels

Stereo channel: 3 channels

Effect type: Echo with three independent volumes

Warning key: CHIME, SIREN

Media player: Bluetooth, folder search, USB port, memory card port, remote control

Entrance port: RCA, TS, USB

Output port: RCA, TS

Cooling fan:

Equipped with a variable speed cooling fan

Power supply: City Power

Required voltage: 220 volts, Body Material: Aluminum, metal

Product weight: 12400 grams

Product dimensions: 483*400*89 mm

Product packaging weight: 13400 grams

Product packaging dimensions: 530*460*160 mm

